



Contemporary  
Lighting™

## Installation Instructions 53310/E53310, 53311/E53311, 53314/E53314 & 53316/E53316 | StarStrand Dimmable Driver

**WARNING: MUST BE USED IN CONJUNCTION WITH A 50% LOAD. DO NOT USE THIS DRIVER WITH LESS THAN A 50% LOAD.**

**WARNING: BE SURE THE ELECTRICITY TO THE WIRE YOU ARE WORKING ON IS SHUT OFF; EITHER THE FUSE REMOVED OR THE CIRCUIT BREAKER OFF.**

**WARNING: USE OF OTHER MANUFACTURERS COMPONENTS WILL VOID WARRANTY, U.I. AND/OR ETL LISTING, AND CREATE A POTENTIAL SAFETY HAZARD.**

**WARNING: RISK OF ELECTRIC SHOCK. NOT SUBMERSIBLE.**

**WARNING: DO NOT ENERGIZE ELECTRICAL SUPPLY CIRCUIT TO DRIVER(S) UNTIL ALL CONNECTIONS HAVE BEEN MADE AND TESTED ACCORDING TO NATIONAL ELECTRICAL CODES AND ALL LOCAL ELECTRICAL CODES. IF YOU ARE UNCLEAR ON HOW TO PROCEED, CONTACT A QUALIFIED ELECTRICIAN.**

**CAUTION: RISK OF FIRE: 12V LED TAPE MUST NOT BE USED IN A 24V SYSTEM, and 24V LED TAPE MUST NOT BE USED IN A 12V SYSTEM**

**CAUTION: THE LOCATION AND NUMBER OF DRIVERS INSTALLED ON RESIDENTIAL CIRCUIT BREAKERS MAY CAUSE THE BREAKERS TO TRIP WHEN THE LIGHTING LOAD IS ENERGIZED. IF THIS OCCURS REPLACE THE RESIDENTIAL CIRCUIT BREAKER WITH A BREAKER RATED FOR HIGH IN-RUSH CURRENT.**


### Driver Installation

Select desired location to mount driver(s). Not in contact with insulation and away from oven or any other source of intense heat and as close as possible to the lighting system to achieve the most efficient operation. Driver(s) can be mounted vertically or horizontally. After firmly mounting the driver(s) select a listed connector (not furnished) appropriate to the type of electrical supply cable at site. Remove cover and knockout from driver(s) and fasten connector to terminal cover and secure in place with connector. If driver is being used in a damp or wet location, ensure any open knockouts and/or connectors are weatherproofed.

**Line Voltage Wiring and Grounding with Required Magnetic Low-Voltage Dimmer**  
See Reverse.

### DRIVER DIAGRAM

*(Drawing for illustration purposes only. May differ from actual driver received)*



Maxim Lighting is a registered trademark and StarStrand and ET2 Contemporary Lighting are trademarks of Maxim Lighting International, Inc. All products, images, designs and logos are © 2011 Maxim Lighting International, Inc. All Rights Reserved.

**REV. D**

For more information or customer service call  
(800) 486-2946, visit [maximlighting.com](http://maximlighting.com) or [et2online.com](http://et2online.com)




Contemporary  
Lighting™

Installation Instructions & Warranty  
53310/E53310, 53311/E53311, 53314/E53314 & 53316/E53316 | StarStrand Dimmable Driver

### Driver Must Be Used With Magnetic Low-Voltage Dimmer

The StarStrand dimmable direct wire driver is dimmed using most MAGNETIC, LOW VOLTAGE dimmer. For a list of compatible dimmers please visit the Maxim Lighting or ET2 Contemporary Lighting Web sites. **NOT USING A DIMMER WITH THIS DRIVER WILL DAMAGE THE TAPE AND VOID THE WARRANTY.**

Connect ground wire from dimmer to green ground wire on the driver(s). Connect wire hot (black) supply from dimmer to black wire on the driver(s). Connect wire neutral (white) supply wire to white wire, bypassing the dimmer.



### 2 YEAR LIMITED WARRANTY

StarStrand™ LED Tape Lighting System components will be warranted for normal use for 2 years while the original purchaser owns it. Normal use means residential non-commercial use for no more than 6 hours per day.

Maxim Lighting and/or ET2 Contemporary Lighting will, at its election, repair, replace or make appropriate adjustment where Maxim Lighting and/or ET2 Contemporary Lighting inspection discloses any such defects occurring in normal usage within two (2) years after date of shipment. Maxim Lighting and/or ET2 Contemporary Lighting is not responsible for removal or installation costs. This warranty is limited to the repair or replacement of the product only and that Maxim Lighting and/or ET2 Contemporary Lighting is not responsible for any labor incurred. Use of incorrect installation methods will void the warranty.

To obtain warranty service contact Maxim Lighting and/or ET2 Contemporary Lighting either through your Dealer, Contractor or E-tailer, or by writing Maxim Lighting International, Attn: Customer Service Department, 253 North Vineland Avenue, City of Industry, CA 95746, USA, or by calling 1-800-486-2946 from within the USA and 1-626-956-4200 outside of the USA.

### DISCLAIMER OF IMPLIED WARRANTY

IMPLIED WARRANTIES INCLUDING THAT OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE EXPRESSLY LIMITED IN DURATION TO THE DURATION OF THIS WARRANTY. MAXIM LIGHTING AND/OR ET2 CONTEMPORARY LIGHTING AND/OR SELLER DISCLAIMS ANY LIABILITY FOR SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES.

Some states/provinces do not allow limitations on how long an implied warranty lasts, or the exclusion or limitation of special, incidental or consequential damages, so these limitations and exclusions may not apply to you. This warranty gives you specific legal rights. You may also have other rights which vary from state/province to state/province.



Maxim Lighting is a registered trademark and StarStrand and ET2 Contemporary Lighting are trademarks of Maxim Lighting International, Inc. All products, images, designs and logos are © 2011 Maxim Lighting International, Inc. All Rights Reserved.

REV. D

For more information or customer service call  
(800) 486-2946, visit [maximlighting.com](http://maximlighting.com) or [et2online.com](http://et2online.com)